

Power Inverters - True Sinewave



Premium Output To Run Your Loads

All modern electronics are designed to run on electricity using a True (Pure) sine waveform, the most reliable waveform available. It is the same waveform the utility company supplies to your home and business. This waveform appears graphically as a smooth wave with peaks and valleys. KISAE True sinewave inverters provide power with very low harmonic distortion, noise or excess heat. These inverters are the preferred choice for powering "sensitive loads" like onboard electronics and demanding motor loads. Some appliances also require a True sinewave to run properly. These include: digital clocks, light dimmers, variable speed motors, flat screen TVs, video game consoles, battery chargers and audio/visual equipment. Because of their advanced features and benefits, True sinewave inverters represent a premium purchase choice.



Power Inverters

True Sine Wave Output - SW Series
 Regulatory Approved
 Commercial / Residential / Leisure Use



Power Inverter	120 VAC Series			230 VAC Series		
	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i

AC Output

	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i
Power (Continuous)	400W	800W	2000W	400W	1000W	2000W
Power (Peak)	800W	1600W	4000W	800W	1600W	4000W
Voltage/Frequency	120VAC / 60 Hz	120VAC / 60 Hz	120VAC / 60 Hz	230VAC / 50 Hz	230VAC / 50 Hz	230VAC / 50 Hz
Current	3.3A	8.3A	16.6A	1.7A	4.3A	8.7A
Waveform	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)
Peak Efficiency	90%	90%	90%	90%	90%	90%
AC Receptacle	NEMA 5-15	NEMA 5-15 GFCI	NEMA 5-20 GFCI	Euro, Australia, UK	Euro, Australia, UK	Euro, Australia, UK

DC Output

5V USB Output	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i
	750mA	2.1A	2.1A	750mA	2.1A	2.1A

DC Input

	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i
Voltage (nominal)	12.5Vdc	12.5Vdc	12.5Vdc	12.5Vdc	12.5Vdc	12.5Vdc
Operation Range	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc
Current (no load)	< 0.3A	< 1.2A	< 1.2A	< 0.8A	< 1.2A	< 1.2A

Display Panel

Indicator	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i
Digital Display (LED)	Power, Fault Not Applicable	Status Input Voltage, Output Power, Warning & Error Code	Status Input Voltage, Output Power, Warning & Error Code	Power, Fault Not Applicable	Status Input Voltage, Output Power, Warning & Error Code	Status Input Voltage, Output Power, Warning & Error Code

Protection

	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i
Input Undervoltage Shutdown	10.5Vdc	10.5Vdc	10.5Vdc	10.5Vdc	10.5Vdc	10.5Vdc
Input Overvoltage Shutdown	15.5Vdc	15.5Vdc	15.5Vdc	15.5Vdc	15.5Vdc	15.5Vdc

Regulatory Compliance

Markings	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i
Conformance	cETLus UL & CSA Standards	cETLus UL & CSA Standards	cETLus UL & CSA Standards	CE LVD, EMC	CE LVD, EMC	CE LVD, EMC



Enclosure

	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i
Weight	3.8 lbs.	6.0 lbs.	11.5 lbs.	1.7 Kg	2.7 Kg	5.2 Kg
Dimension	10.5 x 6.2 x 10.0"	10.5 x 6.2 x 10.0"	14.5 x 10.5 x 14.0"	270 x 160 x 260mm	270 x 160 x 260mm	365 x 370 x 355mm



Accessory (Optional)

Remote ON/OFF switch	SW 1204	SW 1210	SW 1220	SW 1204i	SW 1210i	SW 1220i

Power Inverters

True Sine Wave Output with Transfer Switch - SWXFR Series
 Regulatory Approved
 Commercial / Residential / Leisure Use



SWXFR Series	120 VAC Series			230 VAC Series		
	SWXFR 1210	SWXFR 1220	SWXFR 1230	SWXFR 1210i	SWXFR 1220i	SWXFR 1230i

AC Output

Power (Continuous)	1000W	2000W	3000W	1000W	2000W	3000W
Power (Peak)	2000W	4000W	6000W	2000W	4000W	6000W
Voltage/Frequency	120VAC / 60 Hz	120VAC / 60 Hz	120VAC / 60 Hz	230VAC / 50 Hz	230VAC / 50 Hz	230VAC / 50 Hz
Current	8.3A	16.6A	25.0A	4.3A	8.7A	13.0A
Waveform	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)	True Sine Wave (<3% THD)
Peak Efficiency	90%	90%	90%	90%	90%	90%
AC Receptacle	NEMA 5-15 GFCI	NEMA 5-20 GFCI	NEMA 5-20	Euro, Australia, UK	Euro, Australia, UK	Euro, Australia, UK

DC Output

5V USB Output	2.1A	2.1A	2.1A	2.1A	2.1A	2.1A
---------------	------	------	------	------	------	------

DC Input

Voltage (nominal)	12.5 Vdc	12.5 Vdc	12.5 Vdc	12.5 Vdc	12.5 Vdc	12.5 Vdc
Operation Range	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc	10.5 - 15.5Vdc
Current (no load)	< 1.5A	< 1.5A	< 1.5A	< 1.5A	< 1.5A	< 1.5A

AC Transfer Switch

Transfer Time	< 30ms	< 30ms	< 30ms	< 30ms	< 30ms	< 30ms
Transfer Relay Rating	30A	30A	30A	16A	16A	16A

Display Panel

Indicator	Status	Status
Digital Display (LED)	Input Voltage, Output Power, Warning, Error Code	Input Voltage, Output Power, Warning, Error Code

Protection

Input Undervoltage Shutdown	10.5Vdc	10.5Vdc	10.5Vdc	10.5Vdc	10.5Vdc	10.5Vdc
Input Overvoltage Shutdown	15.5Vdc	15.5Vdc	15.5Vdc	15.5Vdc	15.5Vdc	15.5Vdc

Regulatory Compliance

Markings	cETLus	cETLus	cETLus	CE	CE	CE
Conformance	UL & CSA Standards	UL & CSA Standards	UL & CSA Standards	LVD, EMC	LVD, EMC	LVD, EMC

Enclosure

Weight	11 lbs.	13.0 lbs.	15.4 lbs.	4.9 Kg	5.8 Kg	6.9 Kg
Dimension	17 x 9 x 4.5"	17 x 9 x 4.5"	21 x 9 x 4.5"	435 x 230 x 115mm	435 x 230 x 115mm	539 x 230 x 115mm

